

T.H.22C



TRIODE-HEXODE FREQUENCY CHANGER

OPERATING DATA.

Heater Current	0.2 A.
Heater Voltage	29 V.
Max. Anode Voltage	250 V.
Max. Screen Voltage (Grids 2 and 4) ..	150 V.
Max. Oscillator Anode Voltage	100 V.

APPLICATION.

As Frequency Changer in superheterodyne receivers covering short wavebands. It consists of a hexode mixer and triode oscillator located on a common cathode assembly with adequate screening between each electrode system. It maintains its efficiency excellently at the higher frequencies.

BASE.

Standard 7-pin type. For connections see page 109.

BULB FINISH.

The T.H.22C is supplied with a metallised bulb only.

PRICE 15/-