

MULLARD 4-VOLT VALVES FOR BATTERY SETS

Type.	Description.	Base.	Bulb Finish.	If.	Characteristics at $V_a = 100$; $V_g = 0$.			(a) V_a	(b) V_s or V_{aux}	(c) V_g for (a) or (b)	I_a for (c)	Optimum Load.	Price.
					ra	m	gm						
P.M.14	Screened Tetrode	4-pin	Clear	0.075	230,000	200	0.87	150	75	0	2.75	—	20/-
P.M.3	Medium Impedance Triode ..	4-pin	Clear	0.075	13,000	14	1.05	{ 100 125 150	{ — — —	{ 3.5 4.5 6.0	{ 1.6 2.2 2.8	{ —	{ 8/6
P.M.4DX	Medium Impedance Triode ..	4-pin	Clear	0.1	7,500	15	2.0	{ 100 125 150	{ — — —	{ 1.5-3.0 3.0-4.5 4.5-6.0	{ 1.5 2.0 2.5	{ —	{ 8/6
P.M.4	Output Triode	4-pin	Clear	0.1	4,000	8	2.0	{ 100 125 150	{ — — —	{ 5.0 7.0 8.0	{ 5.5 7.5 10.0	{ 9,000	{ 10/6
P.M.254	Super-power Triode	4-pin	Clear	0.2	2,150	6.5	3.0	{ 100 150 200	{ — — —	{ 9.0 15.0 21.0	{ 6.0 10.0 15.0	{ 6,000	{ 13/6

Page 84

MULLARD 6-VOLT VALVES FOR BATTERY SETS

Type.	Description.	Base.	Bulb Finish.	If.	Characteristics at $V_a = 100$; $V_g = 0$.			(a) V_a	(b) V_s or V_{aux}	(c) V_g for (a) or (b)	I_a for (c)	Optimum Load.	Price.
					ra	m	gm						
P.M.5X	Medium Impedance Triode ..	4-pin	Clear	0.075	14,700	17.5	1.2	{ 100 125 150	{ — — —	{ 1.5-3.0 3.0 3.0-4.5	{ 1.2 1.6 2.0	{ —	{ 8/6
P.M.6D	Medium Impedance Triode ..	4-pin	Clear	0.1	9,000	18.0	2.0	{ 100 125 150	{ — — —	{ 1.5-3.0 3.0-4.5 4.5	{ 1.5 2.0 2.5	{ —	{ 8/6
P.M.6	Output Triode	4-pin	Clear	0.1	3,550	8.0	.25	{ 100 125 150	{ — — —	{ 6.0 7.5 9.0	{ 4.5 7.0 9.5	{ 8,000	{ 10/6